

СБОР ЖУРНАЛА СОБЫТИЙ С BROCADE (SUPPORTSAVE)

Сбор supportSave из CLI коммутатора требует наличия в сети внутреннего FTP/SFTP или SCP-сервера

- 1 Подключитесь к коммутатору под именем **admin**, используя Telnet или SSH
- 2 В командной строке введите: **supportsave**
- 3 Вам будет предложено ввести:
 - IP-адрес вашего FTP-сервера
 - Имя пользователя/пароль для вашего FTP-сервера
 - Выбрать протокол: FTP
 - Удаленный каталог на FTP-сервере
- 4 Сохраните полученный архив

Пример:

```
2498_B40:FID128:admin> supportsave
```

This command collects RASLOG, TRACE, supportShow, core file, FFDC data

and then transfer them to a FTP/SCP/SFTP server or a USB device.

This operation can take several minutes.

NOTE: supportsave will transfer existing trace dump file first, then automatically generate and transfer latest one. There will be two trace dump files transferred after this command.

OK to proceed? (yes, y, no, n): [no] y

Host IP or hostname : 192.168.1.2

Username: user1

Password:

Protocol (ftp | scp | sftp): ftp

Remote Directory: /tmp/switch

Saving support information for switch:2498_B40,
module: RAS...

.....
Saving support information for switch:2498_B40,
module: CTRACE_OLD...

Saving support information for switch:2498_B40,
module: CTRACE_NEW...

Saving support information for switch:2498_B40,
module: FABRIC...

.

.

.

.

Saving support information for switch:2498_B40,
module: RAS_POST...

.....

SupportSave completed.

```
IBM_2498_B40:FID128:admin>
```